

ROTARY DIG DIMMER SW S-PREMIUM 240V 350W

Part Number: HNS626DT



CLICK smart switch
TECHNOLOGY



Features

- Rotary digital dimmer and push button 'on/off' switch in one
- Suits CLIPSAL Saturn and CLIPSAL Saturn Zen style wall plates
- Patented ripple tone rejection
- Perfect for dimmable LED lighting

S-Premium Rotary Digital Dimmer with Built-In ON/OFF Switch

The S-Premium HNS626DT dimmer switch is simple to use and employs a familiar rotary-style dimming method. Turning the knob clockwise will brighten the lights and turning the knob anti-clockwise will decrease brightness. The wider range capability of the HNS626DT provides deep-dimming to zero on most lamps. This versatile 2-in-1 unit also provides push-button ON/OFF control and is the perfect solution for dimmable LED lighting and dimmable compact fluorescent lamps.

The HNS626DT is equipped with timed dimming, a convenient bonus feature that automatically

In support of our policy of continuous product improvement we reserve the right to change materials and specifications without notice. Drawings, where used, are not to scale. All dimensions are in millimetres and sizes given are approximate. Where possible, technical MSDS data sheets are made available on the website. All products should be installed and used in accordance with manufacturer's instructions provided. Warning: products may be the subject of registered designs and patents. Refer to website for terms and conditions on warranty.

dims or brightens lighting. A double tap while lighting is ON will gradually dim lighting over 30 minutes before turning off. Conversely, a double tap when lighting is off will gradually increase brightness to full over 30 minutes. The LED indicator will blink every 5 seconds during timed dimming. The countdown can be cancelled at any time with a sustained 2-second press of the button.

Applications and Compatibility

The HNS626DT is designed for indoor use. It is not rated for outdoor installation. Suggested uses include LED & CFL lighting. NOT SUITABLE FOR FANS AND MOTORS.

For Multi-way dimming and ON/OFF, use the S-Premium HNS026RB Remote Button.

Knobs included to suit Clipsal Saturn and Saturn Zen style wall plates.

Operating Conditions

Operating Voltage: 230-240Va.c. 50Hz

Operating Temperature: 0 to +50 degrees Celsius

Certified Standard: AS/NZS 60669.2.1, CISPR15

Maximum Load: 350W

Minimum Load: 1W

Maximum Current capacity: 1.5A

Note: Operation at temperature, voltage or load outside of the specifications may cause permanent damage to the unit.

The HNS626DT is to be installed as part of a fixed wire electrical installation. By law such installations must be made by an electrical contractor or similarly qualified person. No more than one dimmer can be connected to the same lamp. For operating instructions, important safety warnings and more information, refer to the product User Manual.

Additional Information

C-Tick

[Download C-Tick](#)

Electrical Safety Approval

[Download Electrical Safety Approval](#)

Quick Reference Guide

[Download Quick Reference Guide](#)

Datasheet

[Download Datasheet](#)

In support of our policy of continuous product improvement we reserve the right to change materials and specifications without notice. Drawings, where used, are not to scale. All dimensions are in millimetres and sizes given are approximate. Where possible, technical MSDS data sheets are made available on the website. All products should be installed and used in accordance with manufacturer's instructions provided. Warning: products may be the subject of registered designs and patents. Refer to website for terms and conditions on warranty.

New Product Release Document

[Download New Product Release Document](#)

In support of our policy of continuous product improvement we reserve the right to change materials and specifications without notice. Drawings, where used, are not to scale. All dimensions are in millimetres and sizes given are approximate. Where possible, technical MSDS data sheets are made available on the website. All products should be installed and used in accordance with manufacturer's instructions provided. Warning: products may be the subject of registered designs and patents. Refer to website for terms and conditions on warranty.