

Similar image (Picture shows NT110C)

MCB 1P 10kA C-16A 1M

Architecture

Number of protected poles	1
Number of poles	1 P
Type of pole	1 P
Fixing mode	DIN rail type O (symmetrical)
Curve	С
Functions	
Concurrently switching N-neutral	no
Connectivity	
Top connection alignement for modular devices	Aligned terminal
Bottom connection alignement for modular devices	Aligned terminal
Main electrical features	
Rated short circuit breaking capacity Icn AC accordin IEC60898-1	g 10 kA
Rated operational voltage Ue	240 / 415 V
Type of supply voltage	AC
	50/60 Hz
Frequency	30/00112
Voltage	30,00112
	500 V
Voltage	
Voltage Rated insulation voltage	500 V
Voltage Rated insulation voltage Rated impulse withstand voltage	500 V
Voltage Rated insulation voltage Rated impulse withstand voltage Electric current	500 V 4000 V
Voltage Rated insulation voltage Rated impulse withstand voltage Electric current Rated current	500 V 4000 V
Voltage Rated insulation voltage Rated impulse withstand voltage Electric current Rated current Rated service breaking capacity Ics AC according IEC	500 V 4000 V 16 A 7,5 kA
Voltage Rated insulation voltage Rated impulse withstand voltage Electric current Rated current Rated service breaking capacity Ics AC according IEC 60898-1 min/maxi threshold value of the AC thermal operation Magnetic regulating currrent	500 V 4000 V 16 A 7,5 kA
Voltage Rated insulation voltage Rated impulse withstand voltage Electric current Rated current Rated service breaking capacity Ics AC according IEC 60898-1 min/maxi threshold value of the AC thermal operation	500 V 4000 V 16 A 7,5 kA
Voltage Rated insulation voltage Rated impulse withstand voltage Electric current Rated current Rated service breaking capacity Ics AC according IEC 60898-1 min/maxi threshold value of the AC thermal operation Magnetic regulating current	500 V 4000 V 16 A 7,5 kA 1,13 / 1,45 In 5 / 10 In



Technical Properties	
Rated service breaking capacity Ics under 230V AC	7,5 kA
according IEC 60898-1	
Rated service breaking capacity Ics under 240V AC	7,5 kA
according IEC 60898-1	
Electric current / temperature	
Rating current -25°C	20 A
Rating current -20°C	19,7 A
Rating current -15°C	19,3 A
Rating current -10°C	19 A
Rating current -5°C	18,6 A
Rating current 0°C	18,3 A
Rating current 5°C	17,9 A
Rating current 10°C	17,6 A
Rating current 15°C	17,2 A
Rating current 20°C	16,8 A
Rating current 25°C	16,4 A
Rating current 30°C	16 A
Rating current 35°C	15,6 A
Rating current 40°C	15,2 A
Rating current 45°C	14,7 A
Rating current 50°C	14,3 A
Rating current 55°C	13,8 A
Rating current 60°C	13,3 A
Rating current 65°C	12,9 A
Rating current 70°C	12,4 A
Current correction factors	
-	1 1
Correction factor of rating current for 2 devices placed	<u>.</u> 11
Correction factor of rating current for 2 devices placed side-by-side	
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed	
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side	d 0,95
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices	d 0,95
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side	0,9
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed	0,9
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side	d 0,95 0,9 d 0,85
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz	d 0,95 0,9 d 0,85
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz	1 0,95 0,9 1 0,85 1,1 1,2
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz	d 0,95 0,9 d 0,85
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz	1 0,95 0,9 d 0,85 1,1 1,2 1,5
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency	10,95 0,9 10,85 1,1 1,2 1,5
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz	1 0,95 0,9 d 0,85 1,1 1,2 1,5
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency	10,95 0,9 10,85 1,1 1,2 1,5
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Frequency	10,95 0,9 10,85 1,1 1,2 1,5
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Frequency Power	1 0,95 0,9 d 0,85 1,1 1,2 1,5 1
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Frequency Total power loss under IN	10,95 0,9 10,85 1,1 1,2 1,5 1
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Power Total power loss under IN Power loss per pole at In Endurance	10,95 0,9 10,85 1,1 1,2 1,5 1
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 400 Hz Correction factor of magnetic tripping with 60 Hz Frequency Power Total power loss under IN Power loss per pole at In	10,95 0,9 10,85 1,1 1,2 1,5 1 50 to 60 Hz

_					
D	im	en	SI	0	ns

Depth of installed product	70 mm
Height of installed product	83 mm
Width of installed product	17,5 mm

Installation, mounting

Type of top connection for modular devices	with screw
Tightening torque	2,8Nm
Type of top rail clip for modular devices	NA
Type of bottom rail clip for modular devices	metallic isolated
Type of Bottom Connection for modular devices	Blconnect
Top removability for modular devices	no
Bottom removability for modular devices	no
360° product mounting position	yes

Connection

Connection cross-section of input and output with	1 / 35 mm²
screws, for massive conductors	
Connection cross section of access and exit with	1 / 25 mm²
screws, for flexible conductor	
Type of connection	with screw

Standards

Standard text	IFC 60898-1 AS/NZS 60898-1

Safety

Protection index IP	IP20	
i iotection mack ii	11 20	

Use conditions

-25 70 °C
2
3
2000 m
for all climates
-25 80 °C